

PM-60M Desktop Mini Class D Digital Amplifier with Bluetooth/USB/SD

Product ID: PM-60M



Short Description

Rated power: 60W

With USB/SD/MP3/Bluetooth

2 MIC input, 2 AUX input

4-16 Ω /70V/100V output

Description

This Class D digital desktop mixer amplifier provides 60W output integrated with bluetooth and USB/SD audio player.

? 2 unbalanced MIC (MIC1 has another port of 6.35mm socket on front panel) input, MIC1 has the priority function which overrides other inputs.

? 2 unbalanced AUX input, each with individual volume control, 1 AUX output.

? Treble and bass separated volume control. TREBLE controls the amount of cut or boost of treble frequencies above 10 kHz. BASS controls the amount of cut or boost of bass frequencies below 100 Hz.

? LED indicators on front panel indicate the power and signal.

? LED screen display play status.

? Combined with 4-16?/70V/100V output, only one output can be connected at the same time, connecting more than one may damage the internal parts.

Specification

Model	PM-60M
Rated power	60W
Output terminals	Low impedance: 4-16?, Voltage line:70V(81.7?), 100V(166.7?)
MIC input	600 Ohms(?), 5-10mv, unbalanced
LINE input	LINE: 10K?, 150-470mv, unbalanced
Frequency response	60Hz ~ 15k Hz (± 3 dB)
THD	< 0.5% at 1kHz, 1/3 rated power
S/N (line)	85dB
S/N (Mic)	>72dB
Tone	BASS:100 Hz (± 10 dB) TREBLE:12k Hz (± 10 dB)
Protection	AC fuse, short circuit, overload, high temperature
Power cable	(3×0.5 mm ²)×1.5M (standard)
Power supply	AC110-240V $\pm 10\%$ 50- 60Hz DC24V
Power consumption	75W
Net weight (Kg)	1.80
Gross weight (Kg)	2.50
Dimension (mm)	305(W)×275(D)×72(H)
Packing dimension (mm)	325(W)×290(D)×135(H)

Product Gallery

