


# PM-2813RF Digital AM/FM Tuner

**Product ID:** PM-2813RF



## Short Description

FM/AM tuner  
LCD display  
1U design

## Description

### Description:

? FM frequency range: 87.5 - 108 MHz, AM frequency range: 522 - 1620KHz  
? LCD display  
? 1U design

## Specification

Model	PB-2813RF
Audio output	500mVrms
Output impedance	1K Ohm
Input voltage	AC 220V 60Hz

Power consumption	6W
Memory	60 station
AM	
Frequency range	522-1620 KHz STEPS 9KHz
Sensitivity	16dB
S/N	40dB
Distortion	0.30%
Frequency Response	80Hz-4KHz
FM	
Frequency range	87.5-108MHz STEPS 50KHz
Sensitivity	20dB
S/N ratio	40dB
Distortion	0.20%
Frequency Response	20Hz-20KHz
Antenna Impedance	75 Ohm

## Product Gallery

